

Codici dei principali semiconduttori SMD

Questa tabella riporta i codici alfanumerici che appaiono stampati sul package dei semiconduttori a montaggio superficiale al fine di renderne più semplice l'identificazione nelle fasi di sostituzione o nella riparazione dei circuiti. La tabella integra l'articolo apparso sul numero di aprile 2018 di Radiokit Elettronica al quale si rimanda il lettore per ogni aspetto utile alla migliore consultazione dei dati oltre che per visionare la piedinatura dei dispositivi.

Package	Codice	Tipo	Caratteristiche in breve	Serie del componente
SMB	C250A	Diodo TVS	Vr 250 V	--250A
SMB	C250C	Diodo TVS	Vr 250 V	--250CA
SMB	CKE	Diodo TVS	Vrwm 5 V	--5.0A
SMB	CKEC	Diodo TVS pair	Vrwm 5 V	--5.0CA
SMB	CKG	Diodo TVS	Vrwm 6 V	--6.0A
SMB	CKGC	Diodo TVS pair	Vrwm 6 V	--6.0CA
SMB	CKK	Diodo TVS	Vrwm 6.5 V	--6.5A
SMB	CKKC	Diodo TVS pair	Vrwm 6.5 V	--6.5CA
SMB	CKM	Diodo TVS	Vrwm 7 V	--7.0A
SMB	CKMC	Diodo TVS pair	Vrwm 7 V	--7.0CA
SMB	CKP	Diodo TVS	Vrwm 7.5 V	--7.5A
SMB	CKPC	Diodo TVS pair	Vrwm 7.5 V	--7.5CA
SMB	CKR	Diodo TVS	Vrwm 8 V	--8.0A
SMB	CKRC	Diodo TVS pair	Vrwm 8 V	--8.0CA
SMB	CKT	Diodo TVS	Vrwm 8.5 V	--8.5A
SMB	CKTC	Diodo TVS pair	Vrwm 8.5 V	--8.5CA
SMB	CKV	Diodo TVS	Vrwm 9 V	--9.0A
SMB	CKVC	Diodo TVS pair	Vrwm 9 V	--9.0CA
SMB	CKX	Diodo TVS	Vrwm 10 V	--10A
SMB	CKXC	Diodo TVS pair	Vrwm 10 V	--10CA
SMB	CKZ	Diodo TVS	Vrwm 11 V	--11A
SMB	CKZC	Diodo TVS pair	Vrwm 11 V	--11CA
SMB	CLE	Diodo TVS	Vrwm 12 V	--12A
SMB	CLEC	Diodo TVS pair	Vrwm 12 V	--12CA
SMB	CLG	Diodo TVS	Vrwm 13 V	--13A
SMB	CLGC	Diodo TVS pair	Vrwm 13 V	--13CA
SMB	CLK	Diodo TVS	Vrwm 14 V	--14A
SMB	CLKC	Diodo TVS pair	Vrwm 14 V	--14CA
SMB	CLM	Diodo TVS	Vrwm 15 V	--15A
SMB	CLMC	Diodo TVS pair	Vrwm 15 V	--15CA
SMB	CLP	Diodo TVS	Vrwm 16 V	--16A
SMB	CLPC	Diodo TVS pair	Vrwm 16 V	--16CA
SMB	CLR	Diodo TVS	Vrwm 17 V	--17A
SMB	CLRC	Diodo TVS pair	Vrwm 17 V	--17CA
SMB	CLT	Diodo TVS	Vrwm 18 V	--18A
SMB	CLTC	Diodo TVS pair	Vrwm 18 V	--18CA
SMB	CLV	Diodo TVS	Vrwm 20 V	--20A
SMB	CLVC	Diodo TVS pair	Vrwm 20 V	--20CA
SMB	CLX	Diodo TVS	Vrwm 22 V	--22A
SMB	CLXC	Diodo TVS pair	Vrwm 22 V	--22CA
SMB	CLZ	Diodo TVS	Vrwm 24 V	--24A
SMB	CLZC	Diodo TVS pair	Vrwm 24 V	--24CA
SMB	CME	Diodo TVS	Vrwm 26 V	--26A
SMB	CMEC	Diodo TVS pair	Vrwm 26 V	--26CA
SMB	CMG	Diodo TVS	Vrwm 28 V	--28A
SMB	CMGC	Diodo TVS pair	Vrwm 28 V	--28CA
SMB	CMK	Diodo TVS	Vrwm 30 V	--30A
SMB	CMKC	Diodo TVS pair	Vrwm 30 V	--30CA
SMB	CMM	Diodo TVS	Vrwm 33 V	--33A
SMB	CMMC	Diodo TVS pair	Vrwm 33 V	--33CA
SMB	CMP	Diodo TVS	Vrwm 36 V	--36A

SMB	CMPC	Diodo TVS pair	Vrwm 36 V	--36CA
SMB	CMR	Diodo TVS	Vrwm 40 V	--40A
SMB	CMRC	Diodo TVS pair	Vrwm 40 V	--40CA
SMB	CMT	Diodo TVS	Vrwm 43 V	--43A
SMB	CMTC	Diodo TVS pair	Vrwm 43 V	--43CA
SMB	CMV	Diodo TVS	Vrwm 45 V	--45A
SMB	CMVC	Diodo TVS pair	Vrwm 45 V	--45CA
SMB	CMX	Diodo TVS	Vrwm 48 V	--48A
SMB	CMXC	Diodo TVS pair	Vrwm 48 V	--48CA
SMB	CMZ	Diodo TVS	Vrwm 51 V	--51A
SMB	CMZC	Diodo TVS pair	Vrwm 51 V	--51CA
SMB	CNE	Diodo TVS	Vrwm 54 V	--54A
SMB	CNEC	Diodo TVS pair	Vrwm 54 V	--54CA
SMB	CNG	Diodo TVS	Vrwm 58 V	--58A
SMB	CNGC	Diodo TVS pair	Vrwm 58 V	--58CA
SMB	CNK	Diodo TVS	Vrwm 60 V	--60A
SMB	CNKC	Diodo TVS pair	Vrwm 60 V	--60CA
SMB	CNM	Diodo TVS	Vrwm 64 V	--64A
SMB	CNMC	Diodo TVS pair	Vrwm 64 V	--64CA
SMB	CNP	Diodo TVS	Vrwm 70 V	--70A
SMB	CNPC	Diodo TVS pair	Vrwm 70 V	--70CA
SMB	CNR	Diodo TVS	Vrwm 75 V	--75A
SMB	CNRC	Diodo TVS pair	Vrwm 75 V	--75CA
SMB	CNT	Diodo TVS	Vrwm 78 V	--78A
SMB	CNTC	Diodo TVS pair	Vrwm 78 V	--78CA
SMB	CNV	Diodo TVS	Vrwm 85 V	--85A
SMB	CNVC	Diodo TVS pair	Vrwm 85 V	--85CA
SMB	CNX	Diodo TVS	Vrwm 90 V	--90A
SMB	CNXC	Diodo TVS pair	Vrwm 90 V	--90CA
SMB	CNZ	Diodo TVS	Vrwm 100 V	--100A
SMB	CNZC	Diodo TVS pair	Vrwm 100 V	--100CA
SMB	CPE	Diodo TVS	Vrwm 110 V	--110A
SMB	CPEC	Diodo TVS pair	Vrwm 110 V	--110CA
SMB	CPG	Diodo TVS	Vrwm 120 V	--120A
SMB	CPGC	Diodo TVS pair	Vrwm 120 V	--120CA
SMB	CPK	Diodo TVS	Vrwm 130 V	--130A
SMB	CPKC	Diodo TVS pair	Vrwm 130 V	--130CA
SMB	CPM	Diodo TVS	Vrwm 150 V	--150A
SMB	CPMC	Diodo TVS pair	Vrwm 150 V	--150CA
SMB	CPP	Diodo TVS	Vrwm 160 V	--160A
SMB	CPPC	Diodo TVS pair	Vrwm 160 V	--160CA
SMB	CPR	Diodo TVS	Vrwm 170 V	--170A
SMB	CPRC	Diodo TVS pair	Vrwm 170 V	--170CA
SMC	CBDE	Diodo TVS pair	Vrwm 5 V	--5.0CA
SMC	CBDG	Diodo TVS pair	Vrwm 6 V	--6.0CA
SMC	CBDK	Diodo TVS pair	Vrwm 6.5 V	--6.5CA
SMC	CBDM	Diodo TVS pair	Vrwm 7 V	--7.0CA
SMC	CBDP	Diodo TVS pair	Vrwm 7.5 V	--7.5CA
SMC	CBDR	Diodo TVS pair	Vrwm 8 V	--8.0CA
SMC	CBDT	Diodo TVS pair	Vrwm 8.5 V	--8.5CA
SMC	CBDV	Diodo TVS pair	Vrwm 9 V	--9.0CA
SMC	CBDX	Diodo TVS pair	Vrwm 10 V	--10CA
SMC	CBDZ	Diodo TVS pair	Vrwm 11 V	--11CA
SMC	CBEE	Diodo TVS pair	Vrwm 12 V	--12CA
SMC	CBEG	Diodo TVS pair	Vrwm 13 V	--13CA
SMC	CBEK	Diodo TVS pair	Vrwm 14 V	--14CA
SMC	CBEM	Diodo TVS pair	Vrwm 15 V	--15CA
SMC	CBEP	Diodo TVS pair	Vrwm 16 V	--16CA
SMC	CBER	Diodo TVS pair	Vrwm 17 V	--17CA
SMC	CBET	Diodo TVS pair	Vrwm 18 V	--18CA
SMC	CBEV	Diodo TVS pair	Vrwm 20 V	--20CA
SMC	CBEX	Diodo TVS pair	Vrwm 22 V	--22CA

SMC	CBEZ	Diodo TVS pair	Vrwm 24 V	--24CA
SMC	CBFE	Diodo TVS pair	Vrwm 26 V	--26CA
SMC	CBFG	Diodo TVS pair	Vrwm 28 V	--28CA
SMC	CBFK	Diodo TVS pair	Vrwm 30 V	--30CA
SMC	CBFM	Diodo TVS pair	Vrwm 33 V	--33CA
SMC	CBFP	Diodo TVS pair	Vrwm 36 V	--36CA
SMC	CBFR	Diodo TVS pair	Vrwm 40 V	--40CA
SMC	CBFT	Diodo TVS pair	Vrwm 43 V	--43CA
SMC	CBFV	Diodo TVS pair	Vrwm 45 V	--45CA
SMC	CBFX	Diodo TVS pair	Vrwm 48 V	--48CA
SMC	CBFX	Diodo TVS pair	Vrwm 51 V	--51CA
SMC	CBGE	Diodo TVS pair	Vrwm 54 V	--54CA
SMC	CBGG	Diodo TVS pair	Vrwm 58 V	--58CA
SMC	CBGK	Diodo TVS pair	Vrwm 60 V	--60CA
SMC	CBGM	Diodo TVS pair	Vrwm 64 V	--64CA
SMC	CBGP	Diodo TVS pair	Vrwm 70 V	--70CA
SMC	CBGR	Diodo TVS pair	Vrwm 75 V	--75CA
SMC	CBGT	Diodo TVS pair	Vrwm 78 V	--78CA
SMC	CBGV	Diodo TVS pair	Vrwm 85 V	--85CA
SMC	CBGX	Diodo TVS pair	Vrwm 90 V	--90CA
SMC	CBGZ	Diodo TVS pair	Vrwm 100 V	--100CA
SMC	CBHE	Diodo TVS pair	Vrwm 110 V	--110CA
SMC	CBHG	Diodo TVS pair	Vrwm 120 V	--120CA
SMC	CBHK	Diodo TVS pair	Vrwm 130 V	--130CA
SMC	CBHM	Diodo TVS pair	Vrwm 150 V	--150CA
SMC	CBHP	Diodo TVS pair	Vrwm 160 V	--160CA
SMC	CBHR	Diodo TVS pair	Vrwm 170 V	--170CA
SMC	CGDE	Diodo TVS	Vrwm 5 V	--5.0A
SMC	CGDG	Diodo TVS	Vrwm 6 V	--6.0A
SMC	CGDK	Diodo TVS	Vrwm 6.5 V	--6.5A
SMC	CGDM	Diodo TVS	Vrwm 7 V	--7.0A
SMC	CGDP	Diodo TVS	Vrwm 7.5 V	--7.5A
SMC	CGDR	Diodo TVS	Vrwm 8 V	--8.0A
SMC	CGDT	Diodo TVS	Vrwm 8.5 V	--8.5A
SMC	CGDV	Diodo TVS	Vrwm 9 V	--9.0A
SMC	CGDX	Diodo TVS	Vrwm 10 V	--10A
SMC	CGDZ	Diodo TVS	Vrwm 11 V	--11A
SMC	CGEE	Diodo TVS	Vrwm 12 V	--12A
SMC	CGEG	Diodo TVS	Vrwm 13 V	--13A
SMC	CGEK	Diodo TVS	Vrwm 14 V	--14A
SMC	CGEM	Diodo TVS	Vrwm 15 V	--15A
SMC	CGEP	Diodo TVS	Vrwm 16 V	--16A
SMC	CGER	Diodo TVS	Vrwm 17 V	--17A
SMC	CGET	Diodo TVS	Vrwm 18 V	--18A
SMC	CGEV	Diodo TVS	Vrwm 20 V	--20A
SMC	CGEX	Diodo TVS	Vrwm 22 V	--22A
SMC	CGEZ	Diodo TVS	Vrwm 24 V	--24A
SMC	CGFE	Diodo TVS	Vrwm 26 V	--26A
SMC	CGFG	Diodo TVS	Vrwm 28 V	--28A
SMC	CGFK	Diodo TVS	Vrwm 30 V	--30A
SMC	CGFM	Diodo TVS	Vrwm 33 V	--33A
SMC	CGFP	Diodo TVS	Vrwm 36 V	--36A
SMC	CGFR	Diodo TVS	Vrwm 40 V	--40A
SMC	CGFT	Diodo TVS	Vrwm 43 V	--43A
SMC	CGFV	Diodo TVS	Vrwm 45 V	--45A
SMC	CGFX	Diodo TVS	Vrwm 48 V	--48A
SMC	CGFX	Diodo TVS	Vrwm 51 V	--51A
SMC	CGGE	Diodo TVS	Vrwm 54 V	--54A
SMC	CGGG	Diodo TVS	Vrwm 58 V	--58A
SMC	CGGK	Diodo TVS	Vrwm 60 V	--60A
SMC	CGGM	Diodo TVS	Vrwm 64 V	--64A
SMC	CGGP	Diodo TVS	Vrwm 70 V	--70A

SMC	CGGR	Diodo TVS	Vrwm 75 V	--75A
SMC	CGGT	Diodo TVS	Vrwm 78 V	--78A
SMC	CGGV	Diodo TVS	Vrwm 85 V	--85A
SMC	CGGX	Diodo TVS	Vrwm 90 V	--90A
SMC	CGGZ	Diodo TVS	Vrwm 100 V	--100A
SMC	CGHE	Diodo TVS	Vrwm 110 V	--110A
SMC	CGHG	Diodo TVS	Vrwm 120 V	--120A
SMC	CGHK	Diodo TVS	Vrwm 130 V	--130A
SMC	CGHM	Diodo TVS	Vrwm 150 V	--150A
SMC	CGHP	Diodo TVS	Vrwm 160 V	--160A
SMC	CGHR	Diodo TVS	Vrwm 170 V	--170A
SMC	CHDE	Diodo TVS	Vrwm 5 V	--5.0A
SMC	CHDG	Diodo TVS	Vrwm 6 V	--6.0A
SMC	CHDK	Diodo TVS	Vrwm 6.5 V	--6.5A
SMC	CHDM	Diodo TVS	Vrwm 7 V	--7.0A
SMC	CHDP	Diodo TVS	Vrwm 7.5 V	--7.5A
SMC	CHDR	Diodo TVS	Vrwm 8 V	--8.0A
SMC	CHDT	Diodo TVS	Vrwm 8.5 V	--8.5A
SMC	CHDV	Diodo TVS	Vrwm 9 V	--9.0A
SMC	CHDX	Diodo TVS	Vrwm 10 V	--10A
SMC	CHDZ	Diodo TVS	Vrwm 11 V	--11A
SMC	CHEE	Diodo TVS	Vrwm 12 V	--12A
SMC	CHEG	Diodo TVS	Vrwm 13 V	--13A
SMC	CHEK	Diodo TVS	Vrwm 14 V	--14A
SMC	CHEM	Diodo TVS	Vrwm 15 V	--15A
SMC	CHEP	Diodo TVS	Vrwm 16 V	--16A
SMC	CHER	Diodo TVS	Vrwm 14 V	--17A
SMC	CHET	Diodo TVS	Vrwm 18 V	--18A
SMC	CHEV	Diodo TVS	Vrwm 20 V	--20A
SMC	CHEX	Diodo TVS	Vrwm 22 V	--22A
SMC	CHEZ	Diodo TVS	Vrwm 24 V	--24A
SMC	CHFE	Diodo TVS	Vrwm 26 V	--26A
SMC	CHFG	Diodo TVS	Vrwm 28 V	--28A
SMC	CHFK	Diodo TVS	Vrwm 30 V	--30A
SMC	CHFM	Diodo TVS	Vrwm 33 V	--33A
SMC	CHFP	Diodo TVS	Vrwm 36 V	--36A
SMC	CHFR	Diodo TVS	Vrwm 40 V	--40A
SMC	CHFT	Diodo TVS	Vrwm 43 V	--43A
SMC	CHFV	Diodo TVS	Vrwm 45 V	--45A
SMC	CHFX	Diodo TVS	Vrwm 48 V	--48A
SMC	CHFZ	Diodo TVS	Vrwm 51 V	--51A
SMC	CHGE	Diodo TVS	Vrwm 54 V	--54A
SMC	CHGG	Diodo TVS	Vrwm 58 V	--58A
SMC	CHGK	Diodo TVS	Vrwm 60 V	--60A
SMC	CHGM	Diodo TVS	Vrwm 64 V	--64A
SMC	CHGP	Diodo TVS	Vrwm 70 V	--70A
SMC	CHGR	Diodo TVS	Vrwm 75 V	--75A
SMC	CHGT	Diodo TVS	Vrwm 78 V	--78A
SMC	CHGV	Diodo TVS	Vrwm 85 V	--85A
SMC	CHGX	Diodo TVS	Vrwm 90 V	--90A
SMC	CHGZ	Diodo TVS	Vrwm 100 V	--100A
SMC	CHHE	Diodo TVS	Vrwm 110 V	--110A
SMC	CHHG	Diodo TVS	Vrwm 120 V	--120A
SMC	CHHK	Diodo TVS	Vrwm 130 V	--130A
SMC	CHHM	Diodo TVS	Vrwm 150 V	--150A
SMC	CHHP	Diodo TVS	Vrwm 160 V	--160A
SMC	CHHR	Diodo TVS	Vrwm 170 V	--170A
SMC	CIDE	Diodo TVS pair	Vrwm 5 V	--5.0CA
SMC	CIDG	Diodo TVS pair	Vrwm 6 V	--6.0CA
SMC	CIDK	Diodo TVS pair	Vrwm 6.5 V	--6.5CA
SMC	CIDM	Diodo TVS pair	Vrwm 7 V	--7.0CA
SMC	CIDP	Diodo TVS pair	Vrwm 7.5 V	--7.5CA

SMC	CIDR	Diodo TVS pair	Vrwm 8 V	--8.0CA
SMC	CIDT	Diodo TVS pair	Vrwm 8.5 V	--8.5CA
SMC	CIDV	Diodo TVS pair	Vrwm 9 V	--9.0CA
SMC	CIDX	Diodo TVS pair	Vrwm 10 V	--10CA
SMC	CIDZ	Diodo TVS pair	Vrwm 11 V	--11CA
SMC	CIEE	Diodo TVS pair	Vrwm 12 V	--12CA
SMC	CIEG	Diodo TVS pair	Vrwm 13 V	--13CA
SMC	CIEK	Diodo TVS pair	Vrwm 14 V	--14CA
SMC	CIEM	Diodo TVS pair	Vrwm 15 V	--15CA
SMC	CIEP	Diodo TVS pair	Vrwm 16 V	--16CA
SMC	CIER	Diodo TVS pair	Vrwm 17 V	--17CA
SMC	CIET	Diodo TVS pair	Vrwm 18 V	--18CA
SMC	CIEV	Diodo TVS pair	Vrwm 20 V	--20CA
SMC	CIEX	Diodo TVS pair	Vrwm 22 V	--22CA
SMC	CIEZ	Diodo TVS pair	Vrwm 24 V	--24CA
SMC	CIFE	Diodo TVS pair	Vrwm 26 V	--26CA
SMC	CIFG	Diodo TVS pair	Vrwm 28 V	--28CA
SMC	CIFK	Diodo TVS pair	Vrwm 30 V	--30CA
SMC	CIFM	Diodo TVS pair	Vrwm 33 V	--33CA
SMC	CIFP	Diodo TVS pair	Vrwm 36 V	--36CA
SMC	CIFR	Diodo TVS pair	Vrwm 40 V	--40CA
SMC	CIFT	Diodo TVS pair	Vrwm 43 V	--43CA
SMC	CIFV	Diodo TVS pair	Vrwm 45 V	--45CA
SMC	CIFX	Diodo TVS pair	Vrwm 48 V	--48CA
SMC	CIFZ	Diodo TVS pair	Vrwm 51 V	--51CA
SMC	CIGE	Diodo TVS pair	Vrwm 54 V	--54CA
SMC	CIGG	Diodo TVS pair	Vrwm 58 V	--58CA
SMC	CIGK	Diodo TVS pair	Vrwm 60 V	--60CA
SMC	CIGM	Diodo TVS pair	Vrwm 64 V	--64CA
SMC	CIGP	Diodo TVS pair	Vrwm 70 V	--70CA
SMC	CIGR	Diodo TVS pair	Vrwm 75 V	--75CA
SMC	CIGT	Diodo TVS pair	Vrwm 78 V	--78CA
SMC	CIGV	Diodo TVS pair	Vrwm 85 V	--85CA
SMC	CIGX	Diodo TVS pair	Vrwm 90 V	--90CA
SMC	CIGZ	Diodo TVS pair	Vrwm 100 V	--100CA
SMC	CIHE	Diodo TVS pair	Vrwm 110 V	--110CA
SMC	CIHG	Diodo TVS pair	Vrwm 120 V	--120CA
SMC	CIHK	Diodo TVS pair	Vrwm 130 V	--130CA
SMC	CIHM	Diodo TVS pair	Vrwm 150 V	--150CA
SMC	CIHP	Diodo TVS pair	Vrwm 160 V	--160CA
SMC	CIHR	Diodo TVS pair	Vrwm 170 V	--170CA
SMC / SMB	C100A	Diodo TVS	Vr 100 V	--100A
SMC / SMB	C100C	Diodo TVS	Vr 100 V	--100CA
SMC / SMB	C10A	Diodo TVS	Vr 10 V	--10A
SMC / SMB	C10C	Diodo TVS	Vr 10 V	--10CA
SMC / SMB	C110A	Diodo TVS	Vr 110 V	--110A
SMC / SMB	C110C	Diodo TVS	Vr 110 V	--110CA
SMC / SMB	C11A	Diodo TVS	Vr 11 V	--11A
SMC / SMB	C11C	Diodo TVS	Vr 11 V	--11CA
SMC / SMB	C120A	Diodo TVS	Vr 120 V	--120A
SMC / SMB	C120C	Diodo TVS	Vr 120 V	--120CA
SMC / SMB	C12A	Diodo TVS	Vr 12 V	--12A
SMC / SMB	C12C	Diodo TVS	Vr 12 V	--12CA
SMC / SMB	C130A	Diodo TVS	Vr 130 V	--130A
SMC / SMB	C130C	Diodo TVS	Vr 130 V	--130CA
SMC / SMB	C13A	Diodo TVS	Vr 13 V	--13A
SMC / SMB	C13C	Diodo TVS	Vr 13 V	--13CA
SMC / SMB	C150A	Diodo TVS	Vr 150 V	--150A
SMC / SMB	C150C	Diodo TVS	Vr 150 V	--150CA
SMC / SMB	C15A	Diodo TVS	Vr 15 V	--15A
SMC / SMB	C15C	Diodo TVS	Vr 15 V	--15CA
SMC / SMB	C160A	Diodo TVS	Vr 160 V	--160A

SMC / SMB	C160C	Diodo TVS	Vr 160 V	--160CA
SMC / SMB	C16A	Diodo TVS	Vr 16 V	--16A
SMC / SMB	C16C	Diodo TVS	Vr 16 V	--16CA
SMC / SMB	C170A	Diodo TVS	Vr 170 V	--170A
SMC / SMB	C170C	Diodo TVS	Vr 170 V	--170CA
SMC / SMB	C180A	Diodo TVS	Vr 180 V	--180A
SMC / SMB	C180C	Diodo TVS	Vr 180 V	--180CA
SMC / SMB	C18A	Diodo TVS	Vr 18 V	--18A
SMC / SMB	C18C	Diodo TVS	Vr 18 V	--18CA
SMC / SMB	C200A	Diodo TVS	Vr 200 V	--200A
SMC / SMB	C200C	Diodo TVS	Vr 200 V	--200CA
SMC / SMB	C20A	Diodo TVS	Vr 20 V	--20A
SMC / SMB	C20C	Diodo TVS	Vr 20 V	--20CA
SMC / SMB	C220A	Diodo TVS	Vr 220 V	--220A
SMC / SMB	C220C	Diodo TVS	Vr 220 V	--220CA
SMC / SMB	C22A	Diodo TVS	Vr 22 V	--22A
SMC / SMB	C22C	Diodo TVS	Vr 22 V	--22CA
SMC / SMB	C24A	Diodo TVS	Vr 24 V	--24A
SMC / SMB	C24C	Diodo TVS	Vr 24 V	--24CA
SMC / SMB	C27A	Diodo TVS	Vr 27 V	--27A
SMC / SMB	C27C	Diodo TVS	Vr 27 V	--27CA
SMC / SMB	C30A	Diodo TVS	Vr 30 V	--30A
SMC / SMB	C30C	Diodo TVS	Vr 30 V	--30CA
SMC / SMB	C33A	Diodo TVS	Vr 33 V	--33A
SMC / SMB	C33C	Diodo TVS	Vr 33 V	--33CA
SMC / SMB	C36A	Diodo TVS	Vr 36 V	--36A
SMC / SMB	C36C	Diodo TVS	Vr 36 V	--36CA
SMC / SMB	C39A	Diodo TVS	Vr 39 V	--39A
SMC / SMB	C39C	Diodo TVS	Vr 39 V	--39CA
SMC / SMB	C43A	Diodo TVS	Vr 43 V	--43A
SMC / SMB	C43C	Diodo TVS	Vr 43 V	--43CA
SMC / SMB	C47A	Diodo TVS	Vr 47 V	--47A
SMC / SMB	C47C	Diodo TVS	Vr 47 V	--47CA
SMC / SMB	C51A	Diodo TVS	Vr 51 V	--51A
SMC / SMB	C51C	Diodo TVS	Vr 51 V	--51CA
SMC / SMB	C56A	Diodo TVS	Vr 56 V	--56A
SMC / SMB	C56C	Diodo TVS	Vr 56 V	--56CA
SMC / SMB	C62A	Diodo TVS	Vr 62 V	--62A
SMC / SMB	C62C	Diodo TVS	Vr 62 V	--62CA
SMC / SMB	C68A	Diodo TVS	Vr 68 V	--68A
SMC / SMB	C68C	Diodo TVS	Vr 68 V	--68CA
SMC / SMB	C6V8A	Diodo TVS	Vr 6.8 V	--6.8A
SMC / SMB	C6V8C	Diodo TVS	Vr 6.8 V	--6.8CA
SMC / SMB	C75A	Diodo TVS	Vr 75 V	--75A
SMC / SMB	C75C	Diodo TVS	Vr 75 V	--75CA
SMC / SMB	C7V5A	Diodo TVS	Vr 7.5 V	--7.5A
SMC / SMB	C7V5C	Diodo TVS	Vr 7.5 V	--7.5CA
SMC / SMB	C82A	Diodo TVS	Vr 82 V	--82A
SMC / SMB	C82C	Diodo TVS	Vr 82 V	--82CA
SMC / SMB	C8V2A	Diodo TVS	Vr 8.2 V	--8.2A
SMC / SMB	C8V2C	Diodo TVS	Vr 8.2 V	--8.2CA
SMC / SMB	C91A	Diodo TVS	Vr 91 V	--91A
SMC / SMB	C91C	Diodo TVS	Vr 91 V	--91CA
SMC / SMB	C9V1A	Diodo TVS	Vr 9.1 V	--9.1A
SMC / SMB	C9V1C	Diodo TVS	Vr 9.1 V	--9.1CA
SOD123	CC1	Diodo zener	Vz 2.4 V	--5221B
SOD123	CC2	Diodo zener	Vz 2.5 V	--5222B
SOD123	CC3	Diodo zener	Vz 2.7 V	--5223B
SOD123	CC4	Diodo zener	Vz 2.8 V	--5224B
SOD123	CC5	Diodo zener	Vz 3 V	--5225B
SOD123	CD1	Diodo zener	Vz 3.3 V	--5226B
SOD123	CD2	Diodo zener	Vz 3.6 V	--5227B

SOD123	CD3	Diodo zener	Vz 3.9 V	--5228B
SOD123	CD4	Diodo zener	Vz 4.3 V	--5229B
SOD123	CD5	Diodo zener	Vz 4.7 V	--5230B
SOD123	CE1	Diodo zener	Vz 5.1 V	--5231B
SOD123	CE2	Diodo zener	Vz 5.6 V	--5232B
SOD123	CE3	Diodo zener	Vz 6 V	--5233B
SOD123	CE4	Diodo zener	Vz 6.2 V	--5234B
SOD123	CE5	Diodo zener	Vz 6.8 V	--5235B
SOD123	CF1	Diodo zener	Vz 7.5 V	--5236B
SOD123	CF2	Diodo zener	Vz 8.2 V	--5237B
SOD123	CF3	Diodo zener	Vz 8.7 V	--5238B
SOD123	CF4	Diodo zener	Vz 9.1 V	--5239B
SOD123	CF5	Diodo zener	Vz 10 V	--5240B
SOD123	CH1	Diodo zener	Vz 11 V	--5241B
SOD123	CH2	Diodo zener	Vz 12 V	--5242B
SOD123	CH3	Diodo zener	Vz 13 V	--5243B
SOD123	CH4	Diodo zener	Vz 14 V	--5244B
SOD123	CH5	Diodo zener	Vz 15 V	--5245B
SOD123	CJ1	Diodo zener	Vz 16 V	--5246B
SOD123	CJ2	Diodo zener	Vz 17 V	--5247B
SOD123	CJ3	Diodo zener	Vz 18 V	--5248B
SOD123	CJ4	Diodo zener	Vz 19 V	--5249B
SOD123	CJ5	Diodo zener	Vz 20 V	--5250B
SOD123	CK1	Diodo zener	Vz 22 V	--5251B
SOD123	CK2	Diodo zener	Vz 24 V	--5252B
SOD123	CK3	Diodo zener	Vz 25 V	--5253B
SOD123	CK4	Diodo zener	Vz 27 V	--5254B
SOD123	CK5	Diodo zener	Vz 28 V	--5255B
SOD123	CM1	Diodo zener	Vz 30 V	--5256B
SOD123	CM2	Diodo zener	Vz 33 V	--5257B
SOD123	CM3	Diodo zener	Vz 36 V	--5258B
SOD123	CM4	Diodo zener	Vz 39 V	--5259B
SOD123	CM5	Diodo zener	Vz 43 V	--5260B
SOD123	CN1	Diodo zener	Vz 47 V	--5261B
SOD123	CN2	Diodo zener	Vz 51 V	--5262B
SOD123	CN3	Diodo zener	Vz 56 V	--5263B
SOD123	CN4	Diodo zener	Vz 60 V	--5264B
SOD123	CN5	Diodo zener	Vz 62 V	--5265B
SOD123	CP1	Diodo zener	Vz 68 V	--5266B
SOD123	CP2	Diodo zener	Vz 75 V	--5267B
SOD323	1A8	Diodo zener	Vz 20 V	--5250
SOD323	1B8	Diodo zener	Vz 22 V	--5251
SOD323	1C8	Diodo zener	Vz 24 V	--5252
SOD323	1D8	Diodo zener	Vz 25 V	--5253
SOD323	1E8	Diodo zener	Vz 25 V	--5254
SOD323	1F8	Diodo zener	Vz 28 V	--5255
SOD323	1G8	Diodo zener	Vz 30 V	--5256
SOD323	1H8	Diodo zener	Vz 33 V	--5257
SOD323	1J8	Diodo zener	Vz 36 V	--5258
SOD323	1K8	Diodo zener	Vz 39 V	--5259
SOD323	1L8	Diodo zener	Vz 43 V	--5260
SOD323	1M8	Diodo zener	Vz 47 V	--5261
SOD323	1P	Diodo zener	Vz 18 V	--18L
SOD323	2P	Diodo zener	Vz 20 V	--20L
SOD323	3P	Diodo zener	Vz 22 V	--22L
SOD323	44	Diodo	V_R 100 V, I_F 250 mA max	--4448
SOD323	4P	Diodo zener	Vz 24 V	--24L
SOD323	5P	Diodo zener	Vz 27 V	--27L
SOD323	6P	Diodo zener	Vz 30 V	--30L
SOD323	7N	Diodo zener	Vz 1.8 V	--1L8
SOD323	7P	Diodo zener	Vz 33 V	--33L
SOD323	8A1	Diodo zener	Vz 2.4 V	--5221

SOD323	8AC	Diodo zener	Vz 3.3 V	--5226
SOD323	8B1	Diodo zener	Vz 2.5 V	--5222
SOD323	8BC	Diodo zener	Vz 3.6 V	--5227
SOD323	8C1	Diodo zener	Vz 2.7 V	--5223
SOD323	8CC	Diodo zener	Vz 3.9 V	--5228
SOD323	8D1	Diodo zener	Vz 2.8 V	--5224
SOD323	8DC	Diodo zener	Vz 4.3 V	--5229
SOD323	8E1	Diodo zener	Vz 3 V	--5225
SOD323	8EC	Diodo zener	Vz 4.7 V	--5230
SOD323	8GC	Diodo zener	Vz 5.6 V	--5232
SOD323	8HC	Diodo zener	Vz 6 V	--5233
SOD323	8JC	Diodo zener	Vz 6.2 V	--5234
SOD323	8KC	Diodo zener	Vz 6.8 V	--5235
SOD323	8LC	Diodo zener	Vz 7.5 V	--5236
SOD323	8MC	Diodo zener	Vz 8.2 V	--5237
SOD323	8N	Diodo zener	Vz 2 V	--2L0
SOD323	8NC	Diodo zener	Vz 8.7 V	--5238
SOD323	8P	Diodo zener	Vz 36 V	--36L
SOD323	8PC	Diodo zener	Vz 9.1 V	--5239
SOD323	8QC	Diodo zener	Vz 10 V	--5240
SOD323	8RC	Diodo zener	Vz 11 V	--5241
SOD323	8SC	Diodo zener	Vz 12 V	--5242
SOD323	8TC	Diodo zener	Vz 13 V	--5243
SOD323	8UC	Diodo zener	Vz 14 V	--5244
SOD323	8VC	Diodo zener	Vz 15 V	--5245
SOD323	8WC	Diodo zener	Vz 16 V	--5246
SOD323	8XC	Diodo zener	Vz 17 V	--5247
SOD323	8YC	Diodo zener	Vz 18 V	--5248
SOD323	8ZC	Diodo zener	Vz 19 V	--5249
SOD323	9N	Diodo zener	Vz 2.2 V	--2L2
SOD323	9P	Diodo zener	Vz 39 V	--39L
SOD323	AP	Diodo zener	Vz 2.4 V	--2L4
SOD323	AR	Diodo zener	Vz 43 V	--43L
SOD323	BP	Diodo zener	Vz 2.5 V	--2L5
SOD323	BR	Diodo zener	Vz 47 V	--47L
SOD323	C24	Diodo	V _R 300 V, I _F 225 mA max, tr 50 ns	--2004
SOD323	CP	Diodo zener	Vz 2.7 V	--2L7
SOD323	DP	Diodo zener	Vz 2.8 V	--2L8
SOD323	EP	Diodo zener	Vz 3 V	--3L0
SOD323	FP	Diodo zener	Vz 3.3 V	--3L3
SOD323	GP	Diodo zener	Vz 3.6 V	--3L6
SOD323	HP	Diodo zener	Vz 3.9 V	--3L9
SOD323	JP	Diodo zener	Vz 4.3 V	--4L3
SOD323	KP	Diodo zener	Vz 4.7 V	--4L7
SOD323	LP	Diodo zener	Vz 5.1 V	--5L1
SOD323	NP	Diodo zener	Vz 5.6 V	--5L6
SOD323	OP	Diodo zener	Vz 6.2 V	--6L2
SOD323	PP	Diodo zener	Vz 6.8 V	--6L8
SOD323	QP	Diodo zener	Vz 7.5 V	--7L5
SOD323	RP	Diodo zener	Vz 8.2 V	--8L2
SOD323	SP	Diodo zener	Vz 9.1 V	--9L1
SOD323	TP	Diodo zener	Vz 10 V	--10L
SOD323	UP	Diodo zener	Vz 11 V	--11L
SOD323	VP	Diodo zener	Vz 12 V	--12L
SOD323	X1	Diodo zener	Vz 2.4 V	--5221B
SOD323	X2	Diodo zener	Vz 2.5 V	--5222B
SOD323	X3	Diodo zener	Vz 2.7 V	--5223B
SOD323	X4	Diodo zener	Vz 2.8 V	--5224B
SOD323	X5	Diodo zener	Vz 3 V	--5225B
SOD323	X6	Diodo zener	Vz 3.3 V	--5226B
SOD323	X7	Diodo zener	Vz 3.6 V	--5227B
SOD323	X8	Diodo zener	Vz 3.9 V	--5228B

SOD323	X9	Diodo zener	Vz 4.3 V	--5229B
SOD323	XA	Diodo zener	Vz 4.7 V	--5230B
SOD323	XB	Diodo zener	Vz 5.1 V	--5231B
SOD323	XC	Diodo zener	Vz 5.6 V	--5232B
SOD323	XD	Diodo zener	Vz 6 V	--5233B
SOD323	XE	Diodo zener	Vz 6.2 V	--5234B
SOD323	XF	Diodo zener	Vz 6.8 V	--5235B
SOD323	XG	Diodo zener	Vz 7.5 V	--5236B
SOD323	XH	Diodo zener	Vz 8.2 V	--5237B
SOD323	XJ	Diodo zener	Vz 8.7 V	--5238B
SOD323	XK	Diodo zener	Vz 9.1 V	--5239B
SOD323	XL	Diodo zener	Vz 10 V	--5240B
SOD323	XN	Diodo zener	Vz 11 V	--5241B
SOD323	XO	Diodo zener	Vz 12 V	--5242B
SOD323	XP	Diodo zener	Vz 13 V	--5243B
SOD323	XP	Diodo zener	Vz 13 V	--13L
SOD323	XQ	Diodo zener	Vz 14 V	--5244B
SOD323	XR	Diodo zener	Vz 15 V	--5245B
SOD323	XS	Diodo zener	Vz 16 V	--5246B
SOD323	XT	Diodo zener	Vz 17 V	--5247B
SOD323	XU	Diodo zener	Vz 18 V	--5248B
SOD323	XV	Diodo zener	Vz 19 V	--5249B
SOD323	XX	Diodo zener	Vz 20 V	--5250B
SOD323	XY	Diodo zener	Vz 22 V	--5251B
SOD323	XZ	Diodo zener	Vz 24 V	--5252B
SOD323	Y1	Diodo zener	Vz 25 V	--5253B
SOD323	Y2	Diodo zener	Vz 27 V	--5254B
SOD323	Y3	Diodo zener	Vz 28 V	--5255B
SOD323	Y4	Diodo zener	Vz 30 V	--5256B
SOD323	Y5	Diodo zener	Vz 33 V	--5257B
SOD323	Y6	Diodo zener	Vz 36 V	--5258B
SOD323	Y7	Diodo zener	Vz 39 V	--5259B
SOD323	Y8	Diodo zener	Vz 43 V	--5260B
SOD323	Y9	Diodo zener	Vz 47 V	--5261B
SOD323	YP	Diodo zener	Vz 15 V	CMDZ15L
SOD323	ZP	Diodo zener	Vz 16 V	CMDZ16L
SOD523	04	Diodo	Vr 300 V	--2004
SOD523	48	Diodo	V _R 100 V, I _F 250 mA max	--4448
SOD523	F0	Diodo zener	Vz 5.6 V	--5V6
SOD523	F1	Diodo zener	Vz 2.4 V	--2V4
SOD523	F1A	Diodo zener	Vz 2.6 V	--2V6
SOD523	F2	Diodo zener	Vz 2.7 V	--2V7
SOD523	F3	Diodo zener	Vz 3 V	--3V0
SOD523	F4	Diodo zener	Vz 3.3 V	--3V3
SOD523	F5	Diodo zener	Vz 3.6 V	--3V6
SOD523	F6	Diodo zener	Vz 3.9 V	--3V9
SOD523	F7	Diodo zener	Vz 4.3 V	--4V3
SOD523	F8	Diodo zener	Vz 4.7 V	--4V7
SOD523	F9	Diodo zener	Vz 5.1 V	--5V1
SOD523	H0	Diodo zener	Vz 15 V	--15V
SOD523	H1	Diodo zener	Vz 6.2 V	--6V2
SOD523	H2	Diodo zener	Vz 6.8 V	--6V8
SOD523	H3	Diodo zener	Vz 7.5 V	--7V5
SOD523	H4	Diodo zener	Vz 8.2 V	--8V2
SOD523	H5	Diodo zener	Vz 9.1 V	--9V1
SOD523	H6	Diodo zener	Vz 10 V	--10V
SOD523	H7	Diodo zener	Vz 11 V	--11V
SOD523	H8	Diodo zener	Vz 12 V	--12V
SOD523	H9	Diodo zener	Vz 13 V	--13V
SOD523	J0	Diodo zener	Vz 39 V	--39V
SOD523	J1	Diodo zener	Vz 16 V	--16V
SOD523	J2	Diodo zener	Vz 18 V	--18V

SOD523	J3	Diodo zener	Vz 20 V	--20V
SOD523	J4	Diodo zener	Vz 22 V	--22V
SOD523	J5	Diodo zener	Vz 24 V	--24V
SOD523	J6	Diodo zener	Vz 27 V	--27V
SOD523	J7	Diodo zener	Vz 30 V	--30V
SOD523	J8	Diodo zener	Vz 33 V	--33V
SOD523	J9	Diodo zener	Vz 36 V	--36V
SOD523	K1	Diodo zener	Vz 43 V	--43V
SOD523	L0	Diodo zener	Vz 2.2 V	--2L2
SOD523	L8	Diodo zener	Vz 1.8 V	--1L8
SOD523	L9	Diodo zener	Vz 2 V	--2L0
SOD523	M0	Diodo zener	Vz 5.6 V	--5L6
SOD523	M1	Diodo zener	Vz 2.4 V	--2L4
SOD523	M2	Diodo zener	Vz 2.5 V	--2L5
SOD523	M3	Diodo zener	Vz 2.7 V	--2L7
SOD523	M30	Diodo zener	Vz 3 V	--3L0
SOD523	M4	Diodo zener	Vz 3.3 V	--3L3
SOD523	M5	Diodo zener	Vz 3.6 V	--3L6
SOD523	M6	Diodo zener	Vz 3.9 V	--3L9
SOD523	M7	Diodo zener	Vz 4.3 V	--4L3
SOD523	M8	Diodo zener	Vz 4.7 V	--4L7
SOD523	M9	Diodo zener	Vz 5.1 V	--5L1
SOD523	N0	Diodo zener	Vz 15 V	--15L
SOD523	N1	Diodo zener	Vz 6.2 V	--6L2
SOD523	N2	Diodo zener	Vz 6.8 V	--6L8
SOD523	N3	Diodo zener	Vz 7.5 V	--7L5
SOD523	N4	Diodo zener	Vz 8.2 V	--8L2
SOD523	N5	Diodo zener	Vz 9.1 V	--9L1
SOD523	N6	Diodo zener	Vz 10 V	--10L
SOD523	N7	Diodo zener	Vz 11 V	--11L
SOD523	N8	Diodo zener	Vz 12 V	--12L
SOD523	N9	Diodo zener	Vz 13 V	--13L
SOD523	P0	Diodo zener	Vz 39 V	--39L
SOD523	P1	Diodo zener	Vz 16 V	--16L
SOD523	P2	Diodo zener	Vz 18 V	--18L
SOD523	P3	Diodo zener	Vz 20 V	--20L
SOD523	P4	Diodo zener	Vz 22 V	--22L
SOD523	P5	Diodo zener	Vz 24 V	--24L
SOD523	P6	Diodo zener	Vz 27 V	--27L
SOD523	P7	Diodo zener	Vz 30 V	--30L
SOD523	P8	Diodo zener	Vz 33 V	--33L
SOD523	P9	Diodo zener	Vz 36 V	--36L
SOD523	R1	Diodo zener	Vz 43 V	--43L
SOD523	R2	Diodo zener	Vz 47 V	--47L
SOT143	A61	Diodo doppio	V _R 85 V, I _F 200 mA max, tr 6 ns	BAS28
SOT143	CJP	Diodo doppio	V _R 300 V, I _F 225 mA max, tr 50 ns	BAW101
SOT143	L51	Diodo doppio	V _R 60 V, I _F 200 mA max, tr 6 ns	BAS56
SOT23	1A	Transistor NPN	h _{FE} 220 max, f _T 300 MHz, NF 2 dB	BC846A
SOT23	1B	Transistor NPN	h _{FE} 450 max, f _T 300 MHz, NF 2 dB	BC846B
SOT23	1C	Transistor NPN	h _{FE} 800 max, f _T 300 MHz, NF 2 dB	BC846C
SOT23	1E	Transistor NPN	h _{FE} 220 max, f _T 300 MHz, NF 2 dB	BC847A
SOT23	1F	Transistor NPN	h _{FE} 450 max, f _T 300 MHz, NF 2dB	BC847B
SOT23	1FF	Transistor NPN	BV _{CBO} 180 V, h _{FE} 250 max	--5551
SOT23	1G	Transistor NPN	h _{FE} 800 max, f _T 300 MHz, NF 2dB	BC847C
SOT23	1J	Transistor NPN	h _{FE} 220 max, f _T 300 MHz, NF=2 dB	BC848A
SOT23	1K	Transistor NPN	h _{FE} 450 max, f _T 300 MHz, NF=2 dB	BC848B
SOT23	1L	Transistor NPN	h _{FE} 800 max, f _T 300 MHz, NF=2 dB	BC848C
SOT23	2A	Transistor NPN	h _{FE} 220 max, f _T 300 MHz, NF 1.2 dB	BC849A
SOT23	2B	Transistor NPN	h _{FE} 450 max, f _T 300 MHz, NF 1.2 dB	BC849B
SOT23	2C	Transistor NPN	h _{FE} 800 max, f _T 300 MHz, NF 1.2 dB	BC849C
SOT23	2E	Transistor NPN	h _{FE} 220 max, f _T 300 MHz, NF 1.2 dB	BC850A
SOT23	2F	Transistor NPN	h _{FE} 450 max, f _T 300 MHz, NF 1.2 dB	BC850B

SOT23	2G	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 1.2 dB	BC850C
SOT23	3A	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC856A
SOT23	3B	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC856B
SOT23	3C	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC856C
SOT23	3E	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC857A
SOT23	3F	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC857B
SOT23	3G	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC857C
SOT23	3J	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC858A
SOT23	3K	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC858B
SOT23	3L	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC858C
SOT23	4A	Transistor PNP	h_{FE} 220 max, f_T 150 MHz, NF 1.2dB	BC859A
SOT23	4B	Transistor PNP	h_{FE} 450 max, f_T 150 MHz, NF 1.2dB	BC859B
SOT23	4C	Transistor PNP	h_{FE} 800 max, f_T 150 MHz, NF 1.2dB	BC859C
SOT23	4E	Transistor PNP	h_{FE} 220 max, f_T 150 MHz, NF 1.2dB	BC860A
SOT23	4F	Transistor PNP	h_{FE} 450 max, f_T 150 MHz, NF 1.2dB	BC860B
SOT23	4G	Transistor PNP	h_{FE} 800 max, f_T 150 MHz, NF 1.2dB	BC860C
SOT23	5A	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 250 max	--807-16
SOT23	5B	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 400 max	--807-25
SOT23	5C	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 630 max	--807-40
SOT23	5E	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 250 max	--808-16
SOT23	5F	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 400 max	--808-25
SOT23	5G	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 630 max	--808-40
SOT23	6A	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 250 max	--817-16
SOT23	6B	FET-N	I_{DSS} 5 mA max, $V_{GS(OFF)}$ 0.3-3 V, NF 2.5 dB	--5484
SOT23	6B	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 400 max	--817-25
SOT23	6B1	FET-N	I_{DSS} 10 mA max, $V_{GS(OFF)}$ 0.5-4 V, NF 2 dB	--5485
SOT23	6BG	FET-N	I_{DSS} 15 mA max, $V_{GS(OFF)}$ 2.5-6 V, NF 2.5 dB	--4416A
SOT23	6C	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 630 max	--817-40
SOT23	6E	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 250 max	--818-16
SOT23	6E	FET-P	I_{DSS} 5 mA max, $V_{GS(OFF)}$ 0.7-6 V, NF 2.5 dB	--5460
SOT23	6E1	FET-P	I_{DSS} 9 mA max, $V_{GS(OFF)}$ 1-7.5 V, NF 2.5 dB	--5461
SOT23	6E2	FET-P	I_{DSS} 16 mA max, $V_{GS(OFF)}$ 1.8-9 V, NF 2.5 dB	--5462
SOT23	6F	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 400 max	--818-25
SOT23	6G	FET-N	I_{DSS} 30 mA max, $V_{GS(OFF)}$ 0.5-3 V, t_{OFF} 50 ns	--4393
SOT23	6G	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 630 max	--818-40
SOT23	6H	FET-N	I_{DSS} 20 mA max, $V_{GS(OFF)}$ 2-6 V, NF 2.5 dB	--5486
SOT23	6J	FET-N	I_{DSS} 150 mA max, $V_{GS(OFF)}$ 4-10 V, t_{OFF} 20 ns	--4391
SOT23	6K	FET-N	I_{DSS} 75 mA max, $V_{GS(OFF)}$ 2-5 V, t_{OFF} 35 ns	--4392
SOT23	6T	FET-N	I_{DSS} 60 mA max, $V_{GS(OFF)}$ 2-6.5 V, NF 1.5 dB	--310
SOT23	6V	FET-P	I_{DSS} 100 mA max, $V_{GS(OFF)}$ 5-10 V, t_{OFF} 5 ns	--174
SOT23	6W	FET-P	I_{DSS} 60 mA max, $V_{GS(OFF)}$ 3-6 V, t_{OFF} 10 ns	--175
SOT23	6X	FET-P	I_{DSS} 25 mA max, $V_{GS(OFF)}$ 1-4 V, t_{OFF} 15 ns	--176
SOT23	6Y	FET-P	I_{DSS} 20 mA max, $V_{GS(OFF)}$ 0.8-2.5 V, t_{OFF} 20 ns	--177
SOT23	702	DMOS-N	BV_{DSS} 60 V, $r_{DS(ON)}$ 7.5 Ω max, t_{OFF} 20 ns	--7002
SOT23	8AA	Transistor NPN	h_{FE} 220 max, f_T 300 MHz, NF 2 dB	BC846A
SOT23	8AB	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF 2 dB	BC846B
SOT23	8AC	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 2 dB	BC846C
SOT23	8BA	Transistor NPN	h_{FE} 220 max, f_T 300 MHz, NF 2 dB	BC847A
SOT23	8BB	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF 2dB	BC847B
SOT23	8BC	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 2dB	BC847C
SOT23	8CA	Transistor NPN	h_{FE} 220 max, f_T 300 MHz, NF=2 dB	BC848A
SOT23	8CB	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF=2 dB	BC848B
SOT23	8CC	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF=2 dB	BC848C
SOT23	8DA	Transistor NPN	h_{FE} 220 max, f_T 300 MHz, NF 1.2 dB	BC849A
SOT23	8DB	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF 1.2 dB	BC849B
SOT23	8DC	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 1.2 dB	BC849C
SOT23	8EA	Transistor NPN	h_{FE} 220 max, f_T 300 MHz, NF 1.2 dB	BC850A
SOT23	8EB	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF 1.2 dB	BC850B
SOT23	8EC	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 1.2 dB	BC850C
SOT23	8FA	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 250 max	--817-16
SOT23	8FB	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 400 max	--817-25
SOT23	8FC	Transistor NPN	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 630 max	--817-40

SOT23	8GA	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 250 max	--818-16
SOT23	8GB	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 400 max	--818-25
SOT23	8GC	Transistor NPN	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 630 max	--818-40
SOT23	9AA	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC856A
SOT23	9AB	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC856B
SOT23	9AC	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC856C
SOT23	9BA	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC857A
SOT23	9BB	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC857B
SOT23	9BC	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC857C
SOT23	9CA	Transistor PNP	h_{FE} 220 max, f_T 150MHz, NF 2 dB	BC858A
SOT23	9CB	Transistor PNP	h_{FE} 450 max, f_T 150MHz, NF 2 dB	BC858B
SOT23	9CC	Transistor PNP	h_{FE} 800 max, f_T 150MHz, NF 2 dB	BC858C
SOT23	9DA	Transistor PNP	h_{FE} 220 max, f_T 150 MHz, NF 1.2dB	BC859A
SOT23	9DB	Transistor PNP	h_{FE} 450 max, f_T 150 MHz, NF 1.2dB	BC859B
SOT23	9DC	Transistor PNP	h_{FE} 800 max, f_T 150 MHz, NF 1.2dB	BC859C
SOT23	9EA	Transistor PNP	h_{FE} 220 max, f_T 150 MHz, NF 1.2dB	BC860A
SOT23	9EB	Transistor PNP	h_{FE} 450 max, f_T 150 MHz, NF 1.2dB	BC860B
SOT23	9EC	Transistor PNP	h_{FE} 800 max, f_T 150 MHz, NF 1.2dB	BC860C
SOT23	9FA	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 250 max	--807-16
SOT23	9FB	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 400 max	--807-25
SOT23	9FC	Transistor PNP	BV_{CES} 50 V, I_C 800 mA max, h_{FE} 630 max	--807-40
SOT23	9GA	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 250 max	--808-16
SOT23	9GB	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 400 max	--808-25
SOT23	9GC	Transistor PNP	BV_{CES} 30 V, I_C 800 mA max, h_{FE} 630 max	--808-40
SOT23	AA	Transistor NPN	h_{FE} 220 max, f_T 250 MHz, NF=2 dB	BCW60A
SOT23	AB	Transistor NPN	h_{FE} 310 max, f_T 250 MHz, NF=2 dB	BCW60B
SOT23	ABA	Diodo	V_R 50 V, I_F 250 mA max, t_r 4 ns	--4150
SOT23	AC	Transistor NPN	h_{FE} 460 max, f_T 250 MHz, NF=2 dB	BCW60C
SOT23	AD	Transistor NPN	h_{FE} 630 max, f_T 250 MHz, NF=2 dB	BCW60D
SOT23	AG	Transistor NPN	h_{FE} 220 max, f_T 250 MHz, NF=2 dB	BCX70G
SOT23	AH	Transistor NPN	h_{FE} 310 max, f_T 250 MHz, NF=2 dB	BCX70H
SOT23	AJ	Transistor NPN	h_{FE} 460 max, f_T 250 MHz, NF=2 dB	BCX70J
SOT23	AK	Transistor NPN	h_{FE} 630 max, f_T 250 MHz, NF=2 dB	BCX70K
SOT23	B2	Transistor NPN	h_{FE} 120 max, f_T 500 MHz, t_{OFF} 18 ns	--V52
SOT23	BA	Transistor PNP	h_{FE} 220 max, f_T 250 MHz	BCW61A
SOT23	BB	Transistor PNP	h_{FE} 310 max, f_T 250 MHz	BCW61B
SOT23	BC	Transistor PNP	h_{FE} 460 max, f_T 250 MHz	BCW61C
SOT23	BD	Transistor PNP	h_{FE} 630 max, f_T 250 MHz	BCW61D
SOT23	BF	Transistor PNP	h_{FE} 460 max, f_T 250 MHz, NF 1 dB	BCW61FF
SOT23	BG	Transistor PNP	h_{FE} 220 max, f_T 250 MHz, NF 2 dB	BCX71G
SOT23	BH	Transistor PNP	BV_{CES} 45 V, h_{FE} 310 max, f_T 250 MHz	BCX71H
SOT23	BJ	Transistor PNP	BV_{CES} 45 V, h_{FE} 460 max, f_T 250 MHz	BCX71J
SOT23	BK	Transistor PNP	BV_{CES} 45 V, h_{FE} 630 max, f_T 250 MHz	BCX71K
SOT23	BN	Transistor PNP	h_{FE} 630 max, f_T 250 MHz, NF 1 dB	BCW61FN
SOT23	C1	Transistor PNP	h_{FE} 260 max, f_T 150 MHz	BCW29
SOT23	C1A	Transistor NPN	BV_{CES} 60 V, h_{FE} 300 max, f_T 300 MHz	--3904
SOT23	C1AE	Transistor NPN	BV_{CES} 60 V, h_{FE} 300 max, f_T 300 MHz	--3904E
SOT23	C1D	Transistor NPN	BV_{CES} 300 V, h_{FE} 40	--42
SOT23	C1DE	Transistor NPN	BV_{CES} 350 V, h_{FE} 50	--42E
SOT23	C1G	Transistor NPN	BV_{CES} 80 V, h_{FE} 100	--06
SOT23	C1J	Transistor NPN	BV_{CES} 40 V, h_{FE} 120 max, f_T 500 MHz	--2369
SOT23	C1K	Transistor NPN	h_{FE} 630 max, f_T 100 MHz, NF 3 dB	--6428
SOT23	C1L	Transistor NPN	h_{FE} 1250 max, f_T 100 MHz, NF 3 dB	--6429
SOT23	C1M	Transistor NPN	BV_{CBO} 30 V, h_{FE} 10000 min, f_T 125 MHz	--A13
SOT23	C1N	Transistor NPN	BV_{CBO} 30 V, h_{FE} 20000 min, f_T 125 MHz	--A14
SOT23	C1NE	Transistor NPN	BV_{CBO} 40 V, h_{FE} 40000 min, f_T 125 MHz	--A14E
SOT23	C1P	Transistor NPN	BV_{CBO} 75 V, h_{FE} 300 max, f_T 300 MHz	--2222A
SOT23	C1PE	Transistor NPN	BV_{CBO} 100 V, h_{FE} 300 max, f_T 300 MHz	--2222AE
SOT23	C1Q	Transistor NPN	h_{FE} 900 max, f_T 50 MHz, NF 3 dB	--5088
SOT23	C1R	Transistor NPN	h_{FE} 1200 max, f_T 50 MHz, NF 2 dB	--5089
SOT23	C1U	Transistor NPN	h_{FE} 250 min, NF 3 dB	--2484
SOT23	C1V	Transistor NPN	BV_{CBO} 40 V, h_{FE} 20000 min, f_T 130 MHz	--6427

SOT23	C1X	Transistor NPN	h_{FE} 300 max, f_T 30 MHz, NF 3 dB	--930
SOT23	C1Z	Transistor NPN	BV_{CBO} 350 V, h_{FE} 200 max, f_T 40 MHz	--6517
SOT23	C2	Transistor PNP	h_{FE} 500 max, f_T 150 MHz	BCW30
SOT23	C29	Transistor NPN	BV_{CBO} 100 V, h_{FE} 10000 min, f_T 125 MHz	--A29
SOT23	C2A	Transistor PNP	h_{FE} 300 max, f_T 250 MHz, t_{OFF} 300 ns	--3906
SOT23	C2AE	Transistor PNP	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 250 ns	--3906E
SOT23	C2D	Transistor PNP	BV_{CBO} 300 V, h_{FE} 25, f_T 50 MHz	--A92
SOT23	C2DE	Transistor PNP	BV_{CBO} 350 V, h_{FE} 50, f_T 100 MHz	--A92E
SOT23	C2F	Transistor PNP	BV_{CBO} 60 V, h_{FE} 300 max, f_T 200 MHz	--2907A
SOT23	C2FE	Transistor PNP	BV_{CBO} 90 V, h_{FE} 300 max, f_T 200 MHz	--2907AE
SOT23	C2G	Transistor PNP	BV_{CBO} 80 V, h_{FE} 100 min, f_T 50 MHz	--A56
SOT23	C2J	Transistor PNP	h_{FE} 120 max, f_T 500 MHz, t_{OFF} 35 ns	--3640
SOT23	C2L	Transistor PNP	BV_{CBO} 160 V, h_{FE} 60 min, f_T 100 MHz	--5401
SOT23	C2N	Transistor PNP	h_{FE} 400 max	--404A
SOT23	C2P	Transistor PNP	h_{FE} 500 max, f_T 40 MHz, NF 3 dB	--5086
SOT23	C2Q	Transistor PNP	h_{FE} 800 max, f_T 40 MHz, NF 2 dB	--5087
SOT23	C2R	Transistor NPN	h_{FE} 15 min, f_T 350 MHz, t_{OFF} 25 ns	--3646
SOT23	C2T	Transistor PNP	BV_{CBO} 40 V, h_{FE} 300 max, f_T 200 MHz	--4403
SOT23	C2U	Transistor PNP	BV_{CBO} 30 V, h_{FE} 10000, f_T 125 MHz	--A63
SOT23	C2V	Transistor PNP	BV_{CBO} 30 V, h_{FE} 20000, f_T 125 MHz	--A64
SOT23	C2W	Transistor PNP	BV_{CBO} 80 V, h_{FE} 300 max, f_T 150 MHz	--8599
SOT23	C2X	Transistor NPN	BV_{CBO} 60 V, h_{FE} 300 max, f_T 250 MHz	--4401
SOT23	C2Z	Transistor PNP	BV_{CBO} 350 V, h_{FE} 200 max, f_T 40 MHz	--6520
SOT23	C3A	Transistor NPN	h_{FE} 300 max, f_T 100 MHz, NF 4 dB	--3019
SOT23	C3B	Transistor NPN	h_{FE} 20 min, f_T 600 MHz	--918
SOT23	C3D	Transistor PNP	h_{FE} 60 min, f_T 600 MHz	--H81
SOT23	C3E	Transistor NPN	h_{FE} 60 min, f_T 650 MHz	--H10
SOT23	C3Z	Transistor NPN	BV_{CBO} 450 V, h_{FE} 200 max, f_T 20 MHz	--A44
SOT23	C46	Transistor NPN	BV_{CBO} 450 V, h_{FE} 200 max, f_T 20 MHz	--A46
SOT23	C49	Transistor NPN	BV_{CBO} 80 V, h_{FE} 600 max, f_T 150 MHz	--491E
SOT23	C4A	Transistor PNP	BV_{CBO} 80 V, h_{FE} 300 max, f_T 100 MHz	--4033
SOT23	C59	Transistor PNP	BV_{CBO} 80 V, h_{FE} 600 max, f_T 150 MHz	--591E
SOT23	C5D	Diodo	V_R 100 V, I_F 250 mA max, t_r 4 ns	--914
SOT23	C7	Transistor PNP	h_{FE} 260 max, f_T 150 MHz, NF 1 dB	BCF29
SOT23	C702A	DMOS-N	BV_{DSS} 60 V, $r_{DS(ON)}$ 2 Ω max, t_{OFF} 20 ns	--7002A
SOT23	C7H	Transistor NPN	h_{FE} 25 min, f_T 900 MHz, NF 4.5 dB	--5179
SOT23	C8	Transistor PNP	h_{FE} 500 max, f_T 150 MHz, NF 1 dB	BCF30
SOT23	C94	Transistor PNP	BV_{CBO} 400 V, h_{FE} 200 max, f_T 20 MHz	--A94
SOT23	C96	Transistor PNP	BV_{CBO} 400 V, h_{FE} 200 max, f_T 20 MHz	--A96
SOT23	CKB	Transistor NPN	BV_{CBO} 80 V, h_{FE} 300 max, f_T 150 MHz	--8099
SOT23	D1	Transistor NPN	h_{FE} 220 max, f_T 300 MHz	BCW31
SOT23	D2	Transistor NPN	h_{FE} 450 max, f_T 300 MHz	BCW32
SOT23	D3	Transistor NPN	h_{FE} 800 max, f_T 300 MHz	BCW33
SOT23	D7	Transistor NPN	h_{FE} 450 max, f_T 300 MHz, NF 1.2 dB	BCF32
SOT23	D8	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 1.2 dB	BCF33
SOT23	DA	Transistor PNP	BV_{CBO} 45 V, I_C 800 mA max, h_{FE} 250 max	BCW67A
SOT23	DA2	Diodo	V_R 120 V, I_F 400 mA max, t_r 50 ns	--5001
SOT23	DB	Transistor PNP	BV_{CBO} 45 V, I_C 800 mA max, h_{FE} 400 max	BCW67B
SOT23	DC	Transistor PNP	BV_{CBO} 45 V, I_C 800 mA max, h_{FE} 630 max	BCW67C
SOT23	DF	Transistor PNP	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 250 max	BCW68F
SOT23	DG	Transistor PNP	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 400 max	BCW68G
SOT23	DH	Transistor PNP	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 630 max	BCW68H
SOT23	EA	Transistor NPN	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 250 max	BCW65A
SOT23	EB	Transistor NPN	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 400 max	BCW65B
SOT23	EC	Transistor NPN	BV_{CBO} 60 V, I_C 800 mA max, h_{FE} 630 max	BCW65C
SOT23	EF	Transistor NPN	BV_{CBO} 75 V, I_C 800 mA max, h_{FE} 250 max	BCW66F
SOT23	EG	Transistor NPN	BV_{CBO} 75 V, I_C 800 mA max, h_{FE} 400 max	BCW66G
SOT23	EH	Transistor NPN	BV_{CBO} 75 V, I_C 800 mA max, h_{FE} 630 max	BCW66H
SOT23	FD	Transistor PNP	BV_{CBO} 40 V, h_{FE} 20000, f_T 230 MHz	BCV26
SOT23	FE	Transistor PNP	BV_{CBO} 80 V, h_{FE} 10000, f_T 230 MHz	BCV46
SOT23	FF	Transistor NPN	BV_{CBO} 40 V, h_{FE} 20000, f_T 230 MHz	BCV27
SOT23	FG	Transistor NPN	BV_{CBO} 80 V, h_{FE} 10000, f_T 230 MHz	BCV47

SOT23	FG	Transistor NPN	BV_{CBO} 60 V, h_{FE} 10000, f_T 125 MHz	--A27
SOT23	H1	Transistor PNP	h_{FE} 260 max, f_T 150 MHz	BCW69
SOT23	H2	Transistor PNP	h_{FE} 500 max, f_T 150 MHz	BCW70
SOT23	H3	Transistor PNP	h_{FE} 260 max, f_T 150 MHz	BCW89
SOT23	K1	Transistor NPN	h_{FE} 220 max, f_T 300 MHz	BCW71
SOT23	K2	Transistor NPN	h_{FE} 450 max, f_T 300 MHz	BCW72
SOT23	K3	Transistor NPN	h_{FE} 800 max, f_T 300 MHz	BCW81
SOT23	K7	Transistor NPN	h_{FE} 220 max, f_T 300 MHz	BCV71
SOT23	K8	Transistor NPN	h_{FE} 450 max, f_T 300 MHz	BCV72
SOT23	K9	Transistor NPN	h_{FE} 800 max, f_T 300 MHz, NF 1.2 dB	BCF81
SOT23	L20	Diodo	V_R 90 V, I_F 250 mA max, t_r 50 ns	--1001
SOT23	T1	Transistor PNP	BV_{CBO} 50 V, I_C 1000 mA max, h_{FE} 600 max	BCX17
SOT23	T2	Transistor PNP	BV_{CBO} 30 V, I_C 1000 mA max, h_{FE} 600 max	BCX18
SOT23	T7	Transistor PNP	h_{FE} 300 max, f_T 200 MHz, t_{OFF} 100 ns	BSR15
SOT23	T8	Transistor PNP	h_{FE} 300 max, f_T 200 MHz, t_{OFF} 100 ns	BSR16
SOT23	U1	Transistor NPN	BV_{CBO} 50 V, I_C 1000 mA max, h_{FE} 600 max	BCX19
SOT23	U2	Transistor NPN	BV_{CBO} 30 V, I_C 1000 mA max, h_{FE} 600 max	BCX20
SOT23	U7	Transistor NPN	h_{FE} 300 max, f_T 250 MHz, t_{OFF} 285 ns	BSR13
SOT23	U8	Transistor NPN	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 285 ns	BSR14
SOT23	U9	Transistor NPN	h_{FE} 150 max, f_T 250 MHz, t_{OFF} 225 ns	BSR17
SOT23	U92	Transistor NPN	h_{FE} 300 max, f_T 300 MHz	BSR17A
SOT23	W3	Diodo zener	V_Z 2.4 V	--2V4
SOT23	W4	Diodo zener	V_Z 2.7 V	--2V7
SOT23	W5	Diodo zener	V_Z 3 V	--3V0
SOT23	W6	Diodo zener	V_Z 3.3 V	--3V3
SOT23	W7	Diodo zener	V_Z 3.6 V	--3V6
SOT23	W8	Diodo zener	V_Z 3.9 V	--3V9
SOT23	W9	Diodo zener	V_Z 4.3 V	--4V3
SOT23	Y1	Diodo zener	V_Z 11 V	--C11
SOT23	Y10	Diodo zener	V_Z 27 V	--C27
SOT23	Y11	Diodo zener	V_Z 30 V	--C30
SOT23	Y12	Diodo zener	V_Z 33 V	--C33
SOT23	Y13	Diodo zener	V_Z 36 V	--C36
SOT23	Y14	Diodo zener	V_Z 39 V	--C39
SOT23	Y15	Diodo zener	V_Z 43 V	--C43
SOT23	Y16	Diodo zener	V_Z 47 V	--C47
SOT23	Y2	Diodo zener	V_Z 12 V	--C12
SOT23	Y3	Diodo zener	V_Z 13 V	--C13
SOT23	Y4	Diodo zener	V_Z 15 V	--C15
SOT23	Y5	Diodo zener	V_Z 16 V	--C16
SOT23	Y6	Diodo zener	V_Z 18 V	--C18
SOT23	Y7	Diodo zener	V_Z 20 V	--C20
SOT23	Y8	Diodo zener	V_Z 22 V	--C22
SOT23	Y9	Diodo zener	V_Z 24 V	--C24
SOT23	Z1	Diodo zener	V_Z 4.7 V	--C4V7
SOT23	Z2	Diodo zener	V_Z 5.1 V	--C5V1
SOT23	Z3	Diodo zener	V_Z 5.6 V	--C5V6
SOT23	Z4	Diodo zener	V_Z 6.2 V	--C6V2
SOT23	Z5	Diodo zener	V_Z 6.8 V	--C6V8
SOT23	Z6	Diodo zener	V_Z 7.5 V	--C7V5
SOT23	Z7	Diodo zener	V_Z 8.2 V	--C8V2
SOT23	Z8	Diodo zener	V_Z 9.1 V	--C9V1
SOT23	Z9	Diodo zener	V_Z 10 V	--C10
SOT26	CD6	Coppia NPN-PNP	h_{FE} 600 max, f_T 250 MHz	--D6A
SOT26	X02A	Coppia DMOS-N	BV_{DSS} 60 V, $r_{DS(ON)}$ 2 Ω max, t_{OFF} 20 ns	--7002A
SOT26	X07	Coppia NPN-PNP	h_{FE} 300 max, f_T 300/200 MHz	--2207
SOT26	X1A	Coppia NPN-PNP	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 250 ns	--3904
SOT26	X1P	Coppia NPN-PNP	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 285 ns	--2222A
SOT26	X2A	Coppia PNP-PNP	h_{FE} 300 max, f_T 250 MHz, t_{OFF} 300 ns	--3906
SOT26	X2F	Coppia PNP-PNP	h_{FE} 300 max, f_T 200 MHz, t_{OFF} 100 ns	--2907A
SOT26	X309L	Transistor NPN	BV_{CBO} 45 V, I_C 3000 mA max, h_{FE} 200 min	--3090L
SOT26	X46	Coppia NPN-PNP	h_{FE} 300 max, f_T 300/250 MHz	--3946

SOT26	X709L	Transistor PNP	BV_{CBO} 50 V, I_C 3000 mA max, h_{FE} 200 min	--7090L
SOT323	1AC	Transistor NPN	h_{FE} 300 max, f_T 300 MHz	--3904
SOT323	1PC	Transistor NPN	h_{FE} 300 max, f_T 300 MHz	--2222A
SOT323	1QC	Transistor NPN	h_{FE} 900 max, f_T 50MHz, NF 3 dB	--5088
SOT323	1RC	Transistor NPN	h_{FE} 1200 max, f_T 50MHz, NF 2 dB	--5089
SOT323	2AC	Transistor PNP	h_{FE} 300 max, f_T 250 MHz	--3906
SOT323	2FC	Transistor PNP	BV_{CBO} 60 V, h_{FE} 300 max, f_T 200 MHz	--2907A
SOT323	2PC	Transistor PNP	h_{FE} 500 max, f_T 40 MHz, NF 3 dB	--5086
SOT323	2QC	Transistor PNP	h_{FE} 800 max, f_T 40 MHz, NF 2 dB	--5087
SOT323	5CC	Diodo doppio	V_R 100 V, I_F 200 mA max, t_r 4 ns	--7000
SOT323	8FC	Diodo zener	V_Z 5.1 V	--5231
SOT323	A2C	Diodo doppio	V_R 75 V, I_F 200 mA max, t_r 4 ns	--2836
SOT323	A6C	Diodo doppio	V_R 75 V, I_F 200 mA max, t_r 4 ns	--2838
SOT323	ADA	Diodo	V_R 100 V, I_F 250 mA max, t_r 4 ns	--4448
SOT323	B6D	Diodo doppio	V_R 300 V, I_F 225 mA max, t_r 50 ns	--2004
SOT363	C9M0	Coppia NPN-NPN	f_T 50 MHz, NF 2 dB	--5089
SOT363	K04	Coppia NPN-NPN	h_{FE} 300 max, f_T 300 MHz	--3904
SOT363	K06	Coppia PNP-PNP	h_{FE} 300 max, f_T 250 MHz	--3906
SOT363	K07	Coppia PNP-PNP	h_{FE} 300 max, f_T 200 MHz	--2907A
SOT363	K22	Coppia NPN-NPN	h_{FE} 300 max, f_T 300 MHz	--2222A
SOT363	K46	Coppia NPN-PNP	h_{FE} 300 max, f_T 300/250 MHz	--3946
SOT363	K70	Coppia NPN-PNP	h_{FE} 300 max, f_T 300/200 MHz	--2207
SOT363	K78	Coppia NPN-PNP	h_{FE} 900/800 max, f_T 50/40 MHz	--5078
SOT363	K87	Coppia PNP-PNP	h_{FE} 800 max, f_T 40 MHz, NF 2 dB	--5087
SOT363	K88	Coppia NPN-NPN	h_{FE} 900 max, f_T 50 MHz, NF 3 dB	--5088
SOT523	2CA	Diodo doppio	V_R 75 V, I_F 200 mA max	--2836
SOT523	AC1	Transistor NPN	h_{FE} 300 max, f_T 300 MHz	--3904
SOT523	AC2	Transistor PNP	h_{FE} 300 max, f_T 250 MHz	--3906
SOT523	CC5	Diodo doppio	V_R 100 V, I_F 200 mA max, t_r 4 ns	--7000
SOT523	DAA	Diodo	V_R 100 V, I_F 250 mA max, t_r 4 ns	--4448
SOT523	FC2	Transistor PNP	BV_{CBO} 60 V, h_{FE} 300 max, f_T 200 MHz	--2907A
SOT523	HC7	Transistor NPN	h_{FE} 25 min, f_T 900 MHz, NF 4.5 dB	--5179
SOT523	PC1	Transistor NPN	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 285 ns	--2222A
SOT523	U87	Transistor PNP	h_{FE} 900 max, f_T 100 MHz, NF 3 dB	--5087E
SOT523	U88	Transistor NPN	h_{FE} 900 max, f_T 100 MHz, NF 3 dB	--5088E
SOT563	L02	Coppia DMOS-N	BV_{DSS} 60 V, $r_{DS(ON)}$ 2 Ω max, t_{OFF} 20 ns	--7002A
SOT563	L04	Coppia NPN-NPN	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 250 ns	--3904E
SOT563	L06	Coppia PNP-PNP	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 250 ns	--3906E
SOT563	L07	Coppia PNP-PNP	h_{FE} 300 max, f_T 200 MHz, t_{OFF} 100 ns	--2907A
SOT563	L22	Coppia NPN-NPN	h_{FE} 300 max, f_T 300 MHz, t_{OFF} 285 ns	--2222A
SOT563	L46	Coppia NPN-PNP	h_{FE} 300 max, f_T 300 MHz	--3946E
SOT563	L49	Transistor NPN	BV_{CBO} 80 V, I_C 1000 mA max, h_{FE} 600 max	--491E
SOT563	L59	Transistor PNP	BV_{CBO} 80 V, I_C 1000 mA max, h_{FE} 600 max	--591E
SOT563	L70	Coppia NPN-PNP	h_{FE} 300 max, f_T 300/200 MHz	--2207
SOT563	L78	Coppia NPN-PNP	h_{FE} 900 max, f_T 100 MHz, NF 3 dB	--5078E
SOT563	L87	Coppia PNP-PNP	h_{FE} 900 max, f_T 100 MHz, NF 3 dB	--5087E
SOT563	L88	Coppia NPN-NPN	h_{FE} 900 max, f_T 100 MHz, NF 3 dB	--5088E
SOT89	AA	Transistor PNP	BV_{CES} 45 V, h_{FE} 250 max	BCX51
SOT89	AC	Transistor PNP	BV_{CES} 45 V, h_{FE} 160 max	BCX51-10
SOT89	AD	Transistor PNP	BV_{CES} 45 V, h_{FE} 250 max	BCX51-16
SOT89	AE	Transistor PNP	BV_{CES} 60 V, h_{FE} 250 max	BCX52
SOT89	AG	Transistor PNP	BV_{CES} 60 V, h_{FE} 160 max	BCX52-10
SOT89	AH	Transistor PNP	BV_{CES} 100 V, h_{FE} 250 max	BCX53
SOT89	AK	Transistor PNP	BV_{CES} 100 V, h_{FE} 160 max	BCX53-10
SOT89	AL	Transistor PNP	BV_{CES} 100 V, h_{FE} 250 max	BCX53-16
SOT89	AM	Transistor PNP	BV_{CES} 60 V, h_{FE} 250 max	BCX52-16
SOT89	BA	Transistor NPN	BV_{CES} 45 V, h_{FE} 250 max	BCX54
SOT89	BC	Transistor NPN	BV_{CES} 45 V, h_{FE} 160 max	BCX54-10
SOT89	BD	Transistor NPN	BV_{CES} 45 V, h_{FE} 250 max	BCX54-16
SOT89	BE	Transistor NPN	BV_{CES} 60 V, h_{FE} 250 max	BCX55
SOT89	BG	Transistor NPN	BV_{CES} 60 V, h_{FE} 160 max	BCX55-10
SOT89	BH	Transistor NPN	BV_{CES} 100 V, h_{FE} 250 max, f_T 130 MHz	BCX56

SOT89	BK	Transistor NPN	BV_{CES} 100 V, h_{FE} 160 max, f_T 130 MHz	BCX56-10
SOT89	BL	Transistor NPN	BV_{CES} 100 V, h_{FE} 250 max, f_T 130 MHz	BCX56-16
SOT89	BM	Transistor NPN	BV_{CES} 60 V, h_{FE} 250 max	BCX55-16